

[Click here to return to our DIY projects page.](#)



## Ball Jar Lamp

Materials:

½ Gallon Ball Jar with Lid and Band

40 W Clear Appliance light bulb

¼" Manila Rope or Decorative Chain  
(Optional)

Lamp Socket

Lamp Cord

Cord Switch

Metal File

Quick Clamp Plug

1/8" Hex Nut

1/8" x 1 Thread Nipple

1/8" Screw Collar

Wire Cutter/Stripper

Drill with 2 sizes of bits

Instructions:

Drill hole in center of jar lid the same size as threaded Nipple, Drill 4 smaller holes toward the outside of the lid. (File off the sharp metal edges left from drilling holes)

Put Nipple in hole of lid and screw in place with hex nut on inside and screw collar on outside of lid.

Add jar band to lid.

Cut as much Lamp Cord as you think will be long enough for where you are hanging the lamp.

Put cord through Screw Collar and connect to Lamp Socket.

Screw Lamp Socket to Nipple.

Thread on decorative chain or Rope now before you wire the switch and plug.

Wire the Cord Switch-See instructions on package. (The smooth side of cord is HOT and the ribbed side is NEUTRAL)

Wire the Plug to the end of cord and screw in light bulb to Lamp Socket.

Screw band to Jar and turn on switch to make sure light works.

You are done! Enjoy your fun and inexpensive lamp

Instructions By; Julie Roylance

